

**SYSTEM AND METHOD FOR ANALYZING ACTIVITY OF A BODY**

The present invention claims priority to United States Provisional Application Serial No. 60/265,521 filed on January 31, 2001 entitled "SYSTEM AND METHOD FOR DETECTING AN ACCELERATION OF A BODY".

**RELATED APPLICATIONS**

This patent application is a continuation in part of co-pending United States Patent Application No. 09/909,404 filed July 19, 2001 by Lehrman et al. entitled "System and Method for Detecting Motion of a Body," which is a continuation in part of co-pending United States Patent Application No. 09/396,991 filed September 15, 1999 by Lehrman et al. entitled "Systems For Evaluating Movement of A Body and Methods of Operating The Same" that issued on October 23, 2001 as United States Patent No. 6,307,481. United States Patent Application Nos. 09/909,404 and 09/396,991 are both assigned to the assignee of the present invention. The disclosures in United States Patent Application Nos. 09/909,404 and 09/396,991 are hereby incorporated by reference in the present application as if fully set forth herein.

TECHNICAL FIELD OF THE INVENTION

The present invention relates generally to means for analyzing activity of a body relative to an environment, and, more particularly, relates to systems and methods of operation for evaluating movement of a body to analyze body motion, such as falls, irregular movement, including inactivity, etc.

BACKGROUND OF THE INVENTION

Methods for determining specific movements of a body that use a variety of devices, apparatus and systems are, generally speaking, known. The term "body" is defined broadly hereafter and includes both organic and inorganic objects.

In point of fact, many methods are known for sensing body activity, including both movement and non-movement (i.e., sensed dynamic accelerations, including cessation of movement), as well as, for sensing body movement over time, which is commonly used to determine comparative levels of activity of a monitored body (See, United States Patent Nos. 4,110,741, 4,292,630, 5,045,839, and 5,523,742). These methodologies, however, merely report various levels of body activity, and, simply stated, fail to recognize possible causes for any increased or decreased level of body activity.

In contrast, other methodologies have developed over time for the detection of falls (See also, United States Patent Nos. 4,829,285, 5,477,211, 5,554,975, and 5,751,214). These methodologies are largely based upon the utilization of one or more mechanical switches (e.g., mercury switches) that determine when a body has attained a horizontal position. These methods however fail to discern "normal," or acceptable, changes in levels of body activity. Stated another way, the foregoing fall detection methodologies provide no position change analysis and, therefore, cannot determine whether a change in position, once attained, is acceptable or unacceptable.

For instance, in veterinary applications, it is well known that horses sleep while standing and that their breathing is less effectively if they are lying down, particularly if on a side. If a high value mare in foal lies down for a period of time (i.e., is inactive), there is an appreciable economic risk. Contemporary systems and methodologies do not provide activity monitors that "warn" or "alarm" that the absence of movement within a specific environment is dangerous.

As a further example, if a body under consideration was an extraction pump and the environment were either a sump near a subway station, in addition to monitoring for normal operation, which is very episodic and activated by accumulating water, the

pump should be monitored for inactivity over some period of time as indicia that the pump may be malfunctioning and jeopardizing the nearby subway tunnel. Warning of the absence of activity of machinery, depending upon the environment, can have significant safety, economic, and like effect.

5 Various training methods have been conceived for sensing relative tilt of a body (See, United States Patent Nos. 5,300,921 and 5,430,435), and some such methodologies have employed two-axis accelerometers. The output of these devices, however, have reported only static acceleration of the body (i.e., the position of a body relative to earth within broad limits). It should be appreciated that static acceleration, or gravity, is not the same as a lack of dynamic acceleration (i.e., vibration, body movement, and the like), but is instead a gauge of position. While accelerometers that measure both static and dynamic acceleration are known, their primary use has heretofore been substantially confined to applications directed to measuring one or the other, but not both. For instance, the absence of activity/movement for a period of time for a snowmobile or other all-terrain vehicle in the field may signal an equipment breakdown placing the safety of the user at risk.

It may be seen that the various conventional detectors fall into one of two varieties, those that gauge movement of the body

and those that gauge a body's position by various means, with neither type capable of analyzing body activity to determine whether the same is normal or abnormal; and if abnormal, whether such activity (including inactivity) is so abnormal to be beyond tolerance, for instance, to be damaging, destructive, crippling, harmful, injurious, or otherwise alarming or, possibly, distressing to the body.

None of the methodologies heretofore known have provided a suitable means to evaluate body activity over time and to determine whether such activity is tolerable. Further improvement could thus be utilized.

SUMMARY OF THE INVENTION

To address the above-introduced deficiencies of the prior art, the present invention introduces systems, as well as methods of operating such systems, for evaluating body activity relative to an environment. For the purposes hereof, the term "body" is defined broadly, meaning any organic or inorganic object whose activity (e.g., movement, position, etc.) may suitably be evaluated relative to its environment in accordance with the principles hereof; and where the term "environment" is defined broadly as the conditions and the influences that determine the behavior of the physical system in which the body is located.

An advantageous embodiment of a system that evaluates body activity relative to an environment in accordance herewith includes a processor that is associated with a sensor. In operation, the sensor is associated with the body and operates to repeatedly sense dynamic and static accelerative phenomena of the body. The processor processes the sensed dynamic and static accelerative phenomena as a function of at least one accelerative event characteristic and an environmental representation to thereby determine whether the evaluated body activity is within environmental tolerance. The processor operates to monitor both activity and inactivity relative to the environmental representation. The processor also preferably generates state

indicia while processing the sensed accelerative phenomena, which represents the state of the body within the environment over time.

For the purposes hereof, the term "sensor" is defined broadly, meaning a device that senses one or more absolute values, changes in value, or some combination of the same, of at least the sensed accelerative phenomena. According to an advantageous embodiment, described in detail hereafter, the sensor may be a plural-axis sensor that senses accelerative phenomena and generates an output signal to the processor indicative of measurements of both dynamic and static acceleration of the body in plural axes. The phrase "environmental representation," as used herein, is defined broadly as any mathematical or other suitable depiction, delineation, model or like measured description of the environment associated with the body.

According to this embodiment, the processor receives and processes the output signal. The processor is preferably programmed to distinguish between normal and abnormal accelerative events, and, when an abnormal event is identified, to indicate whether the abnormal event is tolerable, or within tolerance. The processor accordingly operates to monitor both activity and inactivity relative to the environmental representation.

According to a related embodiment, the processor can determine when the evaluated body activity is relatively small to inactive as a function of the environmental representation. If the body activity level remains relatively small to inactive for a threshold time period, then the processor is operable to generate an alarm signal. In an advantageous implementation, as the time period approaches a threshold, the processor is also operable to generate a warning signal. Likewise, if the processor determines a relative increase in body activity, it is also operable to restart (i.e., reset) the time period.

In further embodiments, the processor may be programmed to distinguish other physical characteristics, including temperature, pressure, force, sound, light, relative position, and the like. It should be noted that the relevant environment may be statically or dynamically represented. The sophistication of any such representation may be as complex or as uncomplicated as needed by a given application (e.g., disability, injury, infirmity, relative position, or other organic assistance monitoring; cargo or other transport monitoring; military, paramilitary, or other tactical maneuver monitoring; etc.). It should further be noted that any representation may initially be set to, or reset to, a default, including, for instance, a physically empty space, or vacuum.

Regardless, the principles of the advantageous exemplary



embodiment discussed heretofore need at least one accelerative event characteristic to be represented to enable the processor to determine whether the evaluated body activity is within environmental tolerance, which is again advantageously based upon both dynamic and static acceleration measurements.

5           According to a related advantageous embodiment, the system may be associated with other components or sensing systems. For instance, in an assistance monitoring application, the sensor may repeatedly sense dynamic and static acceleration of the body in the plural axes and generate output signals indicative of the measurements. The processor continuously processes the output signals to distinguish between selected accelerative and non-selected accelerative events (described in detail hereafter) based upon both the dynamic and the static acceleration of the body, and generates state indicia, including tolerance indicia, that is communicated to a monitoring controller.

10  
15  
20           In an advantageous embodiment, the system processes accumulated data for purposes of determining and selectively signaling if a select (e.g., static, dynamic, variable, etc.) amount of activity has not occur over a select (e.g., static, dynamic, variable, etc.) time period. The system may suitably be arranged to signal if (a) relatively low to no activity occurs over a given time period indicating that the associated body may have

suffered a unacceptable event (e.g., a patient suffered a stroke in bed, a prisoner failed to comply with wearing a monitoring system, etc.), or (b) a select level of activity is not occurring over a given time period indicating that the associated body may fail to meet a defined level of activity (e.g., a prescribed regimen of activity required to rehabilitate an injury or to maintain health).

According to another embodiment, the system may suitably be arranged to transmit (e.g., continuously, periodically, etc.) to a remote monitor that cooperates with the processor to (a) make notice/alarm-type decisions, or (b) capture "counts" and other suitable statistics for subsequent evaluation of trends in activity levels (e.g., to identify possible changes in body's level of activity; in the case of equipment, possibly to increase efficiency). Regardless of the purpose, tolerance indicia may suitably be communicated to the monitoring controller for record keeping/statistical purposes, as well as to provide "live" monitoring of the individual subscriber.

Communication between the processor and the controller may be by a wireless network, a wired network, or some suitable combination of the same, and may include the Internet. Preferably, the system generates an alert whenever the monitored subscriber is in "jeopardy," as determined by the system, such as in response to a debilitating fall by the subscriber. In a

further embodiment, the processor is operable to repeatedly generate "heartbeat" indicia that indicates that the system is in an operable state, whereby absence of the same informs the monitoring controller that some other part of the system is malfunctioning.

5           The foregoing has outlined rather broadly the features and technical advantages of the present invention so that those skilled in the art may better understand the DETAILED DESCRIPTION OF THE INVENTION that follows. Additional features and advantages of the invention will be described hereinafter that form the subject of the claims of the invention. Those skilled in the art should appreciate that they may readily use the conception and specific embodiments disclosed as a basis for modifying or designing other structures for carrying out the same purposes of the present invention. Those skilled in the art should also realize that  
10 such equivalent constructions do not depart from the spirit and scope of the invention in its broadest form.

Before undertaking the DETAILED DESCRIPTION OF THE INVENTION, it may be advantageous to set forth definitions of certain words and phrases used throughout this patent document: the terms "include" and "comprise," as well as derivatives thereof, mean inclusion  
20 without limitation; the term "or," is inclusive, meaning and/or; the phrases "associated with" and "associated therewith," as well

as derivatives thereof, and the term "associable" may mean to include, be included within, interconnect with, contain, be contained within, connect to or with, couple to or with, be communicable with, cooperate with, interleave, juxtapose, be proximate to, be bound to or with, have, have a property of, or the like; and the terms "controller" and "processor" mean any device, system or part thereof that controls at least one operation, such a device may be implemented in hardware, firmware or software, or some suitable combination of at least two of the same. It should be noted that the functionality associated with any particular controller/processor may be centralized or distributed, whether locally or remotely. Definitions for certain words and phrases are provided throughout this patent document, those of ordinary skill in the art should understand that in many, if not most instances, such definitions apply to prior, as well as future uses of such defined words and phrases.

BRIEF DESCRIPTION OF THE DRAWINGS

For a more complete understanding of the present invention, and the advantages thereof, reference is now made to the following descriptions taken in conjunction with the accompanying drawings, wherein like numbers designate like objects, and in  
5 which:

FIGURE 1 illustrates an isometric view of an exemplary embodiment of a system that evaluates body activity in accordance with the principles of the present invention;

FIGURE 2 illustrates a block diagram of the exemplary system  
10 set forth with respect to FIGURE 1;

FIGURES 3A to 3D illustrate exemplary strip chart records of output of the sensor introduced in FIGURES 1 and 2 taken during illustrative situations;

FIGURE 4 illustrates an operational flow diagram of an  
15 exemplary method of programming a processor in accordance with a fall detection application of the principles of the present invention;

FIGURE 5 illustrates a functional block diagram of an  
20 alternate sensing system that may suitably be associated with the processor of the present invention;

FIGURE 6 illustrates a perspective view of an exemplary remote receiver unit of the system of this invention;

FIGURE 7 illustrates a functional block diagram of the exemplary receiver unit of FIGURE 6;

FIGURE 8 illustrates an exemplary wireless network that is associated via a wired network, such as the Internet, to a remote monitoring controller according to one embodiment of the present invention; and

FIGURE 9 illustrates an exemplary embodiment of the system of the present invention for evaluating body movement with a plurality of acceleration measuring devices;

FIGURE 10 illustrates the coordinate relationships between a three dimensional Cartesian coordinate system and a three dimensional spherical polar coordinate system;

FIGURE 11 illustrates the orientation of a first plural axis accelerometer in an x-y plane of a three dimensional Cartesian coordinate system and the orientation of a second plural axis accelerometer in a y-z plane of the same Cartesian coordinate system;

FIGURE 12 illustrates an exemplary embodiment of the system of the present invention for evaluating body activity comprising two plural axis accelerometer sensors coupled to a controller;

FIGURE 13 illustrates a flow diagram showing a first portion of an advantageous embodiment of the method of the present invention;

FIGURE 14 illustrates a flow diagram showing a second portion of an advantageous embodiment of the method of the present invention; and

FIGURE 15 illustrates a flow diagram showing a third portion of an alternate advantageous embodiment of the method of the present invention.

DESCRIPTION OF THE INVENTION

FIGURES 1 through 15, discussed below, and the various embodiments used to describe the principles of the present invention in this patent document are by way of illustration only and should not be construed in any way to limit the scope of the invention. Those skilled in the art will understand that the principles of the present invention may be implemented in any suitably arranged system for detecting the motion of a body.

FIGURE 1 illustrates an isometric view of an exemplary embodiment of a system (generally designated 11) that evaluates body activity in accordance with the principles of the present invention, and more particularly that measures and distinguishes selected accelerative events of a body (not shown). As used in this disclosure, the phrases "accelerative events" or "accelerative phenomena" are defined as occurrences of change in velocity of the body (or acceleration), whether in magnitude, direction or both, and including cessation of activity or inactivity.

System 11 includes circuit boards 13 and 15 (connected boards at right angles to one another) that are associated with a housing (generally designated 17) utilizing known mounting techniques. Exemplary housing 17 (and system 11, for that matter), when assembled, is approximately one centimeter thick



and is approximately five centimeters across in any direction.

Housing 17 may comprise, for example, exemplary housing halves 19 and 21 that encase boards 13 and 15, although those skilled in the art will understand that any configuration suitable for a particular implementation of the invention may be arranged.

Exemplary rear half 21 is provided with a clip 23 for associating system 11 with the body (e.g., people, animals, objects of various sorts, etc.). Exemplary clip 23 is shown as a mechanical spring-type clip, but could be any known attachment device or system, including either mechanical or chemical attachment systems, or any other suitable means for associating system 11 with the body.

System 11 includes a processor (shown in FIGURE 2) and a sensor 25. Exemplary sensor 25 operates to sense accelerative phenomena of the body, and is mounted on circuit board 13 with x and y axes, 27 and 29, respectively, oriented thereat (though other orientations could be utilized). Sensor 25 is illustratively shown as a plural-axis (dual shown) acceleration measuring device suitably mounted on a single monolithic integrated circuit (one conventional sensor is an accelerometer available from ANALOG DEVICES, INC., located at One Technology Way, Norwood, Massachusetts, United States of America, namely,

Model No. ADXL202). Sensor 25 includes polysilicon surface-micromachined sensor layer 31 built on top of silicon wafer 33. Polysilicon springs 35 resiliently suspend sensor layer 31 over the surface of wafer 33 providing resistance against acceleration forces. Deflection of the sensor layer is measured using a differential capacitor formed by independent fixed and central plates, the fixed plates driven by one hundred eighty degrees (180°) out of phase square waves having amplitude proportional to acceleration. Signal outputs from each axis of sensor 25 are conditioned (i.e., phase sensitive demodulation and low pass filtering) and presented at analog output nodes. While not utilized in the primary advantageous embodiment of this invention, the ANALOG DEVICES' accelerometer is operable to convert the analog signals to duty cycle modulated ("DCM") signals at a DCM stage providing digital output signals capable of being directly counted at a processor.

While techniques for reconstructing analog signals from the digital output signals may suitably be utilized (e.g., passing the duty cycle signals through an RC filter), thereby allowing use of the digital signal output of a sensor of system 11 hereof, use of the analog signal outputs has been found advantageous due to the increased bandwidth availability (0.01 Hz to 5 kHz, adjustable at capacitors at the output nodes to bandlimit the

nodes implementing low-pass filtering for antialiasing and noise reduction), and the measuring sensitivity that may be attained. A typical noise floor of five hundred micro "g" per Hertz ( $500 \times 10^{-6}$  "g"/Hz) is achieved, thereby allowing signals below five milli "g" ( $5 \times 10^{-3}$  "g") to be resolved for bandwidths below 5 60 Hz. The value "g" is the acceleration of gravity at the surface of the earth (32 feet/sec<sup>2</sup> or 9.8 m/sec<sup>2</sup>).

According to the illustrated embodiment, sensor 25 generates analog output voltage signals corresponding to measurements in the x and y axes, which include both an alternating current (ac) voltage component proportional to G forces (i.e., dynamic acceleration component related to vibrations of sensor layer 31) and a direct current (dc) voltage component proportional to an angle relative to earth (i.e., static acceleration component related to gravity). This open loop acceleration measurement architecture, capable of measuring both static and dynamic acceleration, can thus be utilized to determine position of a body by measuring both the x and y output voltages simultaneously, as well as measure forces of impact experienced by a body. This information comprises state indicia, and utilizing both signal components from both outputs, the sensed accelerative phenomena of the body may subsequently be processed to distinguish a variety of accelerative phenomena and,

ultimately, to selectively act based on the distinctions, as is described in detail hereafter to determine whether the evaluated body activity is normal or abnormal, and, if abnormal, whether the same is within tolerance.

It is noted that the foregoing embodiment has been introduced for illustrative purposes only. In alternate embodiments, any sensor that is capable of sensing accelerative phenomena relative to a body may be used in lieu of, or even in conjunction with, sensor 25. Further, alternate orientations of sensor 25 may be used for different applications. Stated differently, system 11 is operable to evaluate body activity relative to an environment and, in operation, sensor 25 (regardless of configuration or select functional aspects) is associated with the body and operates to repeatedly sense dynamic and static accelerative phenomena of the body. The system, preferably using a suitably arranged processor, processes the sensed phenomena as a function of at least one accelerative event characteristic and a representation of the environment in which the body exists to determine whether the evaluated body activity is within environmental tolerance. The system monitors both activity and inactivity relative to the environmental representation, and preferably generates state indicia while processing the sensed phenomena.

Turning next to FIGURE 2, there is illustrated a block diagram of the exemplary system of FIGURE 1, which includes processing circuitry 39, indicating means 41, power supply 67, and switch 68, along with sensor 25. Exemplary processing circuitry 39 illustratively includes a processor 47 and buffer  
5 amplifiers 43 and 45 that buffer the analog x and y outputs from sensor 25. Exemplary processor 47, which is associated with sensor 25, is capable of processing the sensed accelerative phenomena as a function of at least one accelerative event characteristic and the environmental representation to thereby determine whether an  
10 evaluated body movement is within environmental tolerance. Processor 47 also preferably generates state indicia while processing the sensed accelerative phenomena, which may represent the state of the body within the environment over time. Processor 47 is illustratively associated with a crystal oscillator/clock 49,  
15 switch (DIP) inputs 51, an analog-digital conversion circuitry 53 and a DSP filter 55 (one conventional processor is available from TEXAS INSTRUMENTS, INC., located in Dallas, Texas, United States of America, namely, Model No. MSP430P325).

Exemplary indicating means 41, in response to direction from  
20 processor 47, is operable to accomplish at least one of the following: initiate an alarm event; communicate such state, or tolerance, indicia to a monitoring controller; generate

statistics; etc. Indicating means 41 may take any number of forms, however, for use in system 11 of the present embodiment, stage 41 is an RF transmitter including RF modulator 61 enabled by processor 47. Exemplary data is presented and modulated at modulator 61, amplified at amplifier 63 and transmitted at antenna 65 (to a remote receiver unit as discussed hereinafter).

According to the present embodiment, power for the various components of system 11 is provided by power supply 67, which illustratively is a 3.6 volt lithium ion battery. Low power management may suitably be under the control of processor 47 utilizing exemplary switched/power supply voltage FET switch 68 at sensor 25, which provides power only during sampling cycles, and operates to shut components down during non-use cycles. For instance, processor 47 may be taken off-line when processing is complete, reducing current drain (though alternate approaches and implementations are known in the art and further discussion is beyond the scope of this patent document).

It should be noted that the various circuitry discussed heretofore has been introduced herein for illustrative purposes only. System 11 may be implemented using any suitably arranged computer or other processing system including micro, personal, mini, mainframe or super computers, as well as network combinations of two or more of the same. In point of fact, in

one advantageous embodiment, sensor 25 and processor 47 are not co-located, but rather associated wirelessly. To that end, the principles of the present invention may be implemented in any appropriately arranged device having processing circuitry. Processing circuitry may include one or more conventional processors, programmable logic devices, such as programmable array logic ("PALs") and programmable logic arrays ("PLAs"), digital signal processors ("DSPs"), field programmable gate arrays ("FPGAs"), application specific integrated circuits ("ASICs"), large scale integrated circuits ("LSIs"), very large scale integrated circuits ("VLSIs") or the like, to form the various types of circuitry, processors, controllers or systems described and claimed herein.

Conventional computer system architecture is more fully discussed in THE INDISPENSABLE PC HARDWARE BOOK, by Hans-Peter Messmer, Addison Wesley (2nd ed. 1995) and COMPUTER ORGANIZATION AND ARCHITECTURE, by William Stallings, MacMillan Publishing Co. (3rd ed. 1993); conventional computer, or communications, network design is more fully discussed in DATA NETWORK DESIGN, by Darren L. Spohn, McGraw-Hill, Inc. (1993); conventional data communications is more fully discussed in VOICE AND DATA COMMUNICATIONS HANDBOOK, by Bud Bates and Donald Gregory, McGraw-Hill, Inc. (1996), DATA COMMUNICATIONS PRINCIPLES, by R. D. Gitlin, J. F. Hayes and S. B.

Weinstein, Plenum Press (1992) and THE IRWIN HANDBOOK OF TELECOMMUNICATIONS, by James Harry Green, Irwin Professional Publishing (2nd ed. 1992); and conventional circuit design is more fully discussed in THE ART OF ELECTRONICS, by Paul Horowitz and Winfield Hill, Cambridge University Press (2nd ed. 1991). Each of  
5 the foregoing publications is incorporated herein by reference for all purposes.

Turning next to FIGURES 3A to 3D, illustrated are exemplary strip chart records of output of exemplary sensor 25 of FIGURES 1 and 2 taken during illustrative situations. More particularly,  
10 FIGURES 3A and 3B illustrate the analog signal at the x and y outputs of sensor 25 at an active time, namely, during a fall by a body to the left, and whereas FIGURES 3C and 3D illustrate the analog signal at the x and y outputs of sensor 25 during a fall by a body to the right (the dark blocks indicating an alarm  
15 condition). As can be seen from the exemplary traces, a fall to the left and to the right are both distinguishable by the disruption of a stable position, or normal body movement, by a concussive force followed by a distinctly different ending stable position. According to the illustrative embodiment introduced  
20 herein, the direction of fall is clear from the position of the ending trace at the y outputs. If the fall had been more forward or backward, the x output traces would likewise clearly indicate



the same (this assumes x and y sensor axes orientation as set forth in FIGURE 1). Of course, the same x and y outputs of the sensor 25 may be suitably processed to simply determine position of the body, for instance, such as when a person is lying down, when a box has tipped over, etc.

5           Similarly, when system 11 monitors for inactivity, it operates to identify when the evaluated body activity is relatively small to inactive as a function of the environmental representation and a lack to void of accelerative phenomena. Processor 47 counts or other wise monitors the time period of inactivity. If the body  
10 activity level remains relatively small to inactive for a threshold time period, then processor 47 is operable to generate an alarm signal. In an advantageous implementation, as the time period approaches a threshold, processor 47 is also operable to generate a warning signal. Likewise, if processor 47 determines a relative  
15 increase in body activity, it is also operable to restart (i.e., reset) the time period.

Turning next to FIGURE 4, illustrated is operational flow diagram of an exemplary method (generally designated 400) of programming of processor 47 in accordance with a fall detection  
20 application of the principles of the present invention. For the purposes of illustration, concurrent reference is made to system 11 of FIGURES 1 and 2. It should be noted that this

illustration introduces an exemplary operational method for programming processor 47 for its use as a fall detector, and that suitable alternate embodiments of system 11 for evaluating movement of a body relative to different environments may likewise be implemented in accordance with the principles hereof, such as for relative position, other assistance monitoring, transparent monitoring, tactical maneuver monitoring, etc.

Exemplary method 400 begins and a request for sampling measurements is generated, likely by processor 47 (Step 405), either in response to an executing operations program or upon initiation by a user, possibly remotely from a monitoring controller (discussed with reference to FIGURE 8). Sensor 25 senses x and y acceleration values generating measurement signals at the outputs at sensor 25.

In the present implementation, the measurement signals are converted from analog to digital format and filtered by filter 55 (Step 410; thereby reducing probability that an out-of-tolerance abnormal movement will be determined incorrectly in response to a single sharp impact, such as a collision between mount 17 and a hard surface when sensor 25 is off the body causing a sharp signal spike).

Processor 47 uses direct current (dc) voltage components of the outputs from sensor 25 to determine a last stable position of

the body on which sensor 25 is mounted (Step 415). More particularly, processor 47 repeatedly compares successive input values with immediately preceding input values and, if within tolerance, are added thereto and stored in an accumulator. This is repeated until Z samples have been accumulated and added over  
5 some defined period of time (e.g., one second) or until a received input is out of tolerance, in which case the sampling cycle is reinitiated. When Z samples are accumulated and added, the accumulated value is divided by Z to determine a "last stable" static acceleration average value, which is saved and is  
10 indicative of the last stable position of the body. Sampling and/or sampling cycle rates may be varied, but, while preferably not continuous due to power consumption concerns, should be substantially continual. It is important to note, therefore, that such characteristics may be statically maintained or  
15 dynamically generated.

Processor 47 uses alternating current (ac) voltage components of each output from sensor 25 to check against a G force threshold value set at DIP switch 51 to see if it exceeds the threshold (Step 420 - thus qualifying as a potential fall impact, in the  
20 current example, possibly an intensity in excess of about 2 to 4 G depending upon desired sensitivity). According to the present implementation, if three of these dynamic acceleration measurements

are received in excess of the threshold without five intervening measurements that are less than the threshold, the impact detect flag may be set.

Processor 47 determines a fall by testing a post-impact stream of samples against a tolerance (Step 425; for instance, a selected value of the ac voltage components, for example a value less than about 2 G). Each new sample is tested against the previous sample to see if the position of the body has stabilized. When the position has stabilized to less than the tolerance, W samples are averaged to get the new stable static acceleration average value corresponding to the new stable position.

Processor 47, in response to the value corresponding to the new stable position is shifted indicating a change of body position of 45° or more from the last stable position, classifies the event as a debilitating fall and alert stage 41 is activated (Step 430). A greater stabilization or post-stabilization sample period may be selected to allow more time for an uninjured user to rise without issuance of an alert.

Processor 47, after setting the last stable position, adds the absolute values of the x and y last stable positions together, and, then determines whether the body associated with sensor 25 is lying down if the added value exceeds a value

corresponding to 90° plus or minus twenty five percent (25%) (Step 435). In such case, after a selected time (for example, four seconds) with repeated like values, the laying down detect flag is set. While this flag is set, any impact that exceeds the G force threshold is treated as a debilitating fall (Step 440).

5 The flag is set only as long as the added value continues to indicate that the wearer is lying down.

It should be noted that the foregoing embodiment was introduced for illustrative purposes only and that the present invention broadly introduces systems, as well as methods of operating such systems, that evaluate movement of a body relative to an environment, which in the above-given example is an assistance monitoring environment. An important aspect of the present invention is that processor 47 is operable to process sensed accelerative phenomena as a function of at least one  
10 accelerative event characteristic, and that such characteristics will largely be defined by the specific application. Therefore, system 11, and, more particularly, processor 47, generates state indicia relative the environment of interest, and determines whether the evaluated body movement is within tolerance in the  
15 context of that environment. For instance, "tolerance" would likely be very different for a monitored body of an elderly person with a heart condition, a toddler, a box in a freight car,  
20

a container of combustible gas, etc.

Processor 47 preferably operates to monitor both activity and inactivity relative to the environment and, more particularly, to identify when the evaluated body activity is relatively small to inactive. Processor 47 may suitably monitor the time period of inactivity. If the body activity level remains relatively small to inactive for a threshold time period, then processor 47 is operable to generate an alarm signal, or, preferably, before the threshold is reached, to generate a warning signal. Again, if processor 47 senses an increase in body activity, it may suitably restart or reset the time period.

Turning next to FIGURE 5, illustrated is a functional block diagram of an alternate sensing system (generally designated 71) that may suitably be associated with processor 47 of FIGURES 1, 2, and 4 in accordance with the principles of the present invention. In this embodiment, components utilizable with system 11 are configured again as a human fall monitor/detector, and any or all of these additional monitoring functions may be employed with system 11, such as inactivity monitoring. For purposes of illustration, concurrent reference is made to processor 47 of FIGURES 2 and 4.

Exemplary sensor 71 includes a respiration module 73, which includes a body contact breath sensor 75 (for example a

volumetric sensor, or a near body breath sensor), low pass filter 77 and amplifier 79 providing output signals indicative of respiration rate and vitality to processor 47. The outputs are processed and, when a dangerous respiratory condition is suggested (generates state indicia relative the environment, and  
5 determines whether the evaluated body movement (broadly defined herein to include organic physiologic phenomena) is within environmental tolerance), an identifiable (for example, by signal coding) alarm is sent indicating means 41.

Sensor 71 further includes an ECG module 81, which includes  
10 input electrodes 83 and 85 providing heart rate signals to filters 87 and 89. The filtered signals are amplified at amplifier 91 and band pass filtered at filter 93. The output is amplified at 95 for input to processor 47 and processed so that dangerous heart rhythms and events can be detected (generates  
15 state indicia relative the environment, and determines whether the evaluated body movement is within environmental tolerance) and an identifiable alarm sent at alert stage 41.

Sensor 71 further includes a panic button module 97 that is operable using a standard user activated switch 99 positioned at  
20 housing 17 allowing a user to initiate a call for help. The switch output is input to processor 47 to initiate an identifiable alarm at alert stage 41.

Turning momentarily to FIGURES 6 and 7, illustrated are a perspective view of an exemplary remote receiver unit of the system of this invention and a functional block diagram of the same. In a distributed system in accord with one embodiment of this invention, a remote receiver unit 103 (for example a wall mountable unit) as shown in FIGURES 6 and 7 is provided for receipt of transmissions from sensor 25 and/or system 71. Unit 103 includes a receiver antenna 105, indicator LEDs 107 (including indicators for as many detector functions as are employed in the specific embodiment of the apparatus being monitored, as well as an indicator for unit on/off status), and a user interface input keypad 111 for unit setup, reset and alarm deactivation. Power access 113 is provided at the bottom of the unit.

RF receiver 115 is tuned to receive alarm transmissions from sensor 71 and presents the signal received for processing at processor 117 for alarm identification and appropriate output. Processor 117 also receives inputs from keypad 111 and power switch 119. Non-volatile memory 121 is provided for input of identification of the user and/or of the apparatus being monitored. Audible alarm 123, LED bank 107 and retransmission unit 125 (an autodialer, imbedded digital cellular technology, RF transmitter, an Internet appliance, or the like) are connected to



receive outputs from processor 117.

When a transmission is received, or when battery power at the body mounted apparatus is low, an audible alarm is sounded and the appropriate LED (indicative of the condition causing the alarm, for example a debilitating fall by a user of apparatus 11) is activated. If not disabled by the user at key pad 111 within a short period, processor 117 activates retransmission unit 125 initiating a call for help or other remote notification. Similarly, if processor 117 determines that body activity level has remained relatively small to inactive for near to or at a threshold time period, then processor 117 is operable to respectively generate one of a warning signal and an alarm signal. If not disabled by the user at key pad 111 within a short period, processor 117 again activates retransmission unit 125 initiating a call for help or other remote notification.

Operational setup of unit 103 is also accomplished under programming at processor 117 and by sequential operation by a user or technician of keypad 111 and/or power switch 119 as is known (including user ID set, learn mode operations, reset or reprogramming operations, and urgency code operations).

Turning next to FIGURE 8, illustrated is an exemplary hybrid wireless/wired network (generally designated 800) that is associated with a remote monitoring controller 805 according to

one embodiment of the present invention. The wireless network 810 is introduced for illustrative purposes only, and comprises a plurality of cell sites 821 to 823, each containing one of the base stations, BS 801, BS 802, or BS 803. Base stations 801 to 803 are operable to communicate with a plurality of mobile stations (MS) including MS 103 (remote receiver unit 103), and MS 811, MS 812 and MS 814. Mobile stations MS 103, and MS 811, MS 812 and MS 814, may be any suitable cellular devices, including conventional cellular telephones, PCS handset devices, portable computers, metering devices, transceivers, and the like (including, for instance, remote receiver unit 103).

Dotted lines show the approximate boundaries of the cell sites 821 to 823 in which base stations 801 to 803 are located. The cell sites are shown approximately circular for the purposes of illustration and explanation only. It should be clearly understood that the cell sites also may have irregular shapes, depending on the cell configuration selected and natural and man-made obstructions.

In one embodiment of the present invention, BS 801, BS 802, and BS 803 may comprise a base station controller (BSC) and a base transceiver station (BTS). Base station controllers and base transceiver stations are well known to those skilled in the art. A base station controller is a device that manages wireless

communications resources, including the base transceiver station, for specified cells within a wireless communications network. A base transceiver station comprises the RF transceivers, antennas, and other electrical equipment located in each cell site. This equipment may include air conditioning units, heating  
5 units, electrical supplies, telephone line interfaces, and RF transmitters and RF receivers, as well as call processing circuitry. For the purpose of simplicity and clarity in explaining the operation of the present invention, the base transceiver station in each of cells 821, 822, and 823 and the  
10 base station controller associated with each base transceiver station are collectively represented by BS 801, BS 802 and BS 803, respectively.

BS 801, BS 802 and BS 803 transfer voice and data signals between each other and the public telephone system (not shown)  
15 via communications line 831 and mobile switching center (MSC) 840. Mobile switching center 840 is well known to those skilled in the art. Mobile switching center 840 is a switching device that provides services and coordination between the subscribers in a wireless network and external networks 850, such  
20 as the Internet, public telephone system, etc. Communications line 831 may be any suitable connection means, including a T1 line, a T3 line, a fiber optic link, a network backbone

connection, and the like. In some embodiments of the present invention, communications line 831 may be several different data links, where each data link couples one of BS 801, BS 802, or BS 803 to MSC 840.

5 In the exemplary wireless network 800, MS 811 is located in cell site 821 and is in communication with BS 801, MS 103 is located in cell site 822 and is in communication with BS 802, and MS 814 is located in cell site 823 and is in communication with BS 803. MS 812 is also located in cell site 821, close to the edge of cell site 823. The direction arrow proximate MS 812 indicates the movement of MS 812 towards cell site 823.

10 For the purposes of illustration, it is assumed that system 11 is associated with an elderly person whose residence is wirelessly monitored. It is further assumed that sensor 25 is associated with the elderly person and that processor 47 is coupled in MS/remote receiver unit 103, such that sensor 25 and processor 47 are wirelessly associated. System 11 monitors both body activity and inactivity relative to the environmental representation.

15 System 11 repeatedly senses various physiological phenomena of the elderly person, including accelerative phenomena of his body. Remote processor 47 processes the repeatedly sensed phenomena, and, particularly, the accelerative phenomena of the

body, as a function of at least one accelerative event characteristic to thereby determine whether the evaluated body movement is within environmental tolerance. Processor 47 advantageously generates state indicia while processing the sensed accelerative phenomena, representing the state of the body within the environment over time (i.e., environmental representation).

Exemplary processor 47 is programmed to distinguish between normal and abnormal accelerative events (e.g., walking, sitting, lying down, etc. versus tripping, falling down, inactivity over time, etc.), and, when an abnormal event is identified, indicates whether the abnormal event is tolerable, or within tolerance. Processor 47 may also suitably be programmed to distinguish other physical characteristics, including temperature, pressure, force, sound, light, relative position (including lying down), and the like.

As processor 47 generates state indicia, which includes tolerance indicia, it uses the same to determine whether the evaluated body movement is within environmental tolerance. Preferably, such tolerance indicia is compared with at least one threshold, likely associated with the accelerative event characteristic. In response to such comparison, processor 47 controls a suitable indicating means to initiate an alarm event

(locally and via network 810 to monitoring controller 805), to communicate such tolerance indicia to a monitoring controller 805, to generate statistics (locally and via network 810 to monitoring controller 805), or the like.

According to a related advantageous embodiment, such state  
5 indicia, and other information is communicated from time to time to monitoring controller 805, from which such information may suitably be perceived. For instance, a technician, medical professional, or relative might wish to review the activities and status of the elderly person. This may easily be facilitated via  
10 a centralized data repository accessible via the Internet, or via any other suitably arranged network. While viewing such information, the technician, medical professional, or relative (subscriber 2, generally designated 855) might initiate a diagnostic equipment check, a physiological test, a simple status  
15 check, or the like. Similarly, monitoring controller 805, via the network 800, may monitor a "heartbeat" signal generated periodically by MS/remote receiver unit 103, the heartbeat indicating that unit 103 is functional.

FIGURE 9 is a schematic drawing of an alternate advantageous  
20 embodiment 900 of the present invention. As shown in FIGURE 9 sensor 25 of embodiment 900 comprises three acceleration measuring devices 910, 920 and 930. The number three is

illustrative only. It is clear that sensor 25 comprises a plurality of acceleration measuring devices and is not limited to a particular number of acceleration measuring devices. Further, sensor 25 as monitored within system 11 may suitably operate to monitor activity and inactivity relative to an environment.

5           Acceleration measuring devices 910, 920 and 930 may each comprises a plural axis measuring device of the type previously described. For convenience, the acceleration measuring devices will be referred to as accelerometers.

10           Accelerometers 910, 920 and 930 are each connected to controller 940. Controller 940 comprises processing circuitry 39 (including processor 47), indicating means 41, power supply 67 and switch 68, of the types previously described.

15           As shown in FIGURE 9, accelerometer 910, accelerometer 920, and accelerometer 930 are each coupled directly to controller 940. As an electrical circuit connection, it is said that accelerometer 910 and accelerometer 920 are connected to controller 940 in an electrically parallel connection. The connections of accelerometer 910 and accelerometer 920 to controller 940 are not geometrically parallel to each other. In  
20           at least one advantageous embodiment of the present invention the connections of accelerometer 910 and accelerometer 920 to controller 940 are located at right angles with respect to each

other. The combination of accelerometer 920 and accelerometer 930 and the combination of accelerometer 910 and accelerometer 930 are similarly arranged.

5 In one arrangement of this advantageous embodiment of the present invention, accelerometer 910 is aligned parallel to the x-axis of a three dimensional Cartesian coordinated system and is capable of measuring accelerations in the x direction. Accelerometer 920 is aligned parallel to the y-axis and is capable of measuring accelerations in the y direction. Accelerometer 930 is aligned parallel to the z-axis and is capable of measuring acceleration in the z direction.

10  
15  
20 Controller 940 is capable of simultaneously determining the values of acceleration measured by each of accelerometers 910, 920 and 930. In this manner, controller 940 can determine the values of acceleration in x, y and z directions. Processor 47 in controller 940 is capable of adding the values of acceleration in the x, y and z directions to obtain a vector sum (i.e., magnitude and direction) of the body (not shown) to which accelerometers 910, 920 and 930 are attached. It is noted that although embodiment 900 has been described for use with a three dimensional Cartesian coordinate system, other three dimensional coordinate systems may also be used.

For example, FIGURE 10 illustrates a three dimensional



spherical polar coordinate system having coordinates  $R$ ,  $\Theta$ ,  $\Phi$ . FIGURE 10 also illustrates the relationships between a Cartesian coordinate system superimposed on the spherical polar coordinate system. The coordinate  $R$  is radial coordinate. The magnitude of  $R$  equals the distance from the origin of the coordinate system to the end of a vector that originates at the origin. The coordinate  $\Theta$  is an angular coordinate that measures the angle between the vector and the  $z$  axis. The coordinate  $\Phi$  is measured in the plane formed by the vector and the  $z$  axis. The coordinate  $\Phi$  is an angular coordinate that measures the angle between the  $x$  axis and the projection of the vector on the  $x$ - $y$  plane. The coordinate  $\Phi$  is measured in the  $x$ - $y$  plane.

As is shown in FIGURE 10, the relationships between the Cartesian coordinates and the spherical polar coordinates are given by:

$$x = R \sin \Theta \cos \Phi \quad (1)$$

$$y = R \sin \Theta \sin \Phi \quad (2)$$

$$z = R \cos \Theta \quad (3)$$

The values of  $R$ ,  $\Theta$ ,  $\Phi$  may be calculated from the values  $x$ ,  $y$ ,  $z$  by the formulas:

$$R = [x^2 + y^2 + z^2]^{1/2} \quad (4)$$

$$\Theta = \tan^{-1} [ [x^2 + y^2]^{1/2} / z ] \quad (5)$$

$$\Phi = \tan^{-1} [ y / x ] \quad (6)$$

As previously mentioned, a plurality of accelerometers may be used. Although each accelerometer 910, 920 and 930 is shown in FIGURE 9 as a single accelerometer, this arrangement is illustrative only. Each accelerometer 920, 920 and 930 may be replaced with two or more accelerometers (not shown). In other words, additional accelerometers (now shown) may be used in addition to accelerometers 910, 920 and 930 shown in FIGURE 9. The additional accelerometers may be oriented in any chosen direction and are not limited to being in the same plane as one of the accelerometers 910, 920 and 930 (or in the same plane as one of the additional accelerometers). In general, accelerometers comprising sensor 25 may be coupled in series, in parallel, or in a combination of series and parallel connections.

Accelerometer 910 is capable of generating analog output voltage signals corresponding to measurements of acceleration in the x direction. Similarly, accelerometer 920 is capable of generating analog output voltage signals corresponding to measurements of acceleration in the y direction and accelerometer 930 is capable of generating analog output voltage signals corresponding to measurements of acceleration in the z direction.

The analog output voltage signals of accelerometer 910, 920 and 930 each comprise both an alternating current (ac) voltage component proportional to G forces (i.e., dynamic acceleration

component related to vibrations of sensor layer 31 of sensor 25) and a direct current (dc) voltage component proportional to an angle relative to earth (i.e., static acceleration component related to gravity "g").

5 The direct current (dc) voltage components from accelerometers 910, 920 and 930 (representing static acceleration due to gravity in their respective x, y and z directions) may be combined to obtain a value of the acceleration that the body experiences due to gravity. In general, the vector R represents the resultant of combining the x, y and z components of acceleration experienced by the body. When a body is at rest (i.e., dynamic acceleration is zero), the vector R represents the static acceleration due to gravity.

10 Because the value of gravity at the earth's surface is substantially constant for any point on the surface of the earth, the value of gravitational acceleration (obtained by vectorially summing the gravitational acceleration components) will be the same for each measurement. That is, the vector sum of each set of gravitational acceleration components will always give the same total value of gravitational acceleration experienced by the body as long as the body is at rest (or moving at a constant speed) relative to an inertial frame of reference. This value is the gravitational acceleration of approximately thirty two feet per

second per second ( $32 \text{ ft/sec}^2$ ) or approximately nine and eight tenths meters per second per second ( $9.8 \text{ m/sec}^2$ ). This value is customarily referred to as one "g."

Processor 47 in controller 940 is capable of being programmed to sound an alarm condition when controller 940 receives signals from accelerometers 910, 920 and 930 that exceed an alarm limit set in accordance with pre-programmed instructions. In this manner, controller 940 can identify when the body to which accelerometers 910, 920 and 930 have been coupled has experienced an acceleration that exceeds a specified value.

Likewise, processor 47 is capable of being programmed to sound a warning or alarm condition when controller 940 fails to receive appreciable signals from accelerometers 910, 920 and 930 that indicate any activity. If processor 47 determines that the activity level as sensed by accelerometers 910, 920 and 930 has remained relatively small to inactive for near to or at a threshold time period, then processor 47 is operable to respectively generate one of a warning signal and an alarm signal as previously described.

Processor 47 is capable of combining the alternating current (ac) voltage components from accelerometers 910, 920 and 930 (representing dynamic acceleration due to external forces in

their respective x, y and z directions) and the direct current (dc) voltage components from accelerometers 910, 920 and 930 (representing static acceleration due to gravity in their respective x, y and z directions) to obtain a total value of the acceleration that the body experiences (due to dynamic  
5 acceleration and due to gravity). Because the value of acceleration due to gravity will always be equal to one "g", any total value of acceleration that exceeds one "g" will be caused by the presence of dynamic acceleration on the body.

10 In an advantageous embodiment of the present invention, processor 47 is programmed to sound an alarm condition when controller 940 receives signals from accelerometers 910, 920 and 930 that indicate that the total value of acceleration detected exceeds one "g." In this manner, controller 940 determines that the body has experienced dynamic acceleration due to external  
15 forces because the measured acceleration has exceeded the "background" acceleration reading that is always present from gravitational acceleration.

20 Controller 940 receives the total acceleration signal in the x direction from accelerometer 910, and the total acceleration signal in the y direction from accelerometer 920, and the total acceleration signal in the z direction from accelerometer 930. Controller 940 then combines the total acceleration components to

obtain the total acceleration experienced by the body. Controller 940 then subtracts the value of one "g" from the total acceleration. If the result is greater than zero, then controller 940 has determined that the body has experienced dynamic acceleration due to external forces. Controller 940 then sends  
5 an alarm signal in the manner previously described.

In an alternate advantageous embodiment of the present invention, a first plural axis accelerometer 910 and a second plural axis accelerometer 920 are coupled to controller 940 in the orientations shown in FIGURE 11. Accelerometer 910 is aligned as shown in frame 1110. The first axis of accelerometer 910 is aligned parallel to the x axis and the second axis of accelerometer is aligned parallel to the y axis. Accelerometer 920 is aligned as shown in frame 1120. The first axis of accelerometer 920 is aligned parallel to the negative y axis and  
10 the second axis of accelerometer 920 is aligned parallel to the  
15 z axis.

An advantage is to be gained by aligning accelerometer 910 and accelerometer 920 in this manner. When accelerometer 910 and accelerometer 920 share a common axis it is possible to scale out  
20 any inconsistencies between the readings of the two accelerometers. For example, assume that it is known that a force exists in the y direction. Then the force in the y direction

will be the same for both of the two accelerometers. Assume that accelerometer 910 gives a reading of "1.0" for the y direction force and that accelerometer 920 gives a reading of "0.9" for the y direction force. If it is determined that accelerometer 910 has the correct reading, then accelerometer 920 can be  
5 "scaled up" (i.e., corrected) to compensate for inconsistencies in the manufacture of accelerometer 920.

FIGURE 12 illustrates an exemplary embodiment of the present invention in which accelerometer 910 and accelerometer 920 are coupled to controller 940. Accelerometer 910 measures  
10 accelerations of the body in the positive x direction and in the positive y direction. Accelerometer 920 measures accelerations of the body in the negative y direction and in the positive z direction.

The analog x signal from accelerometer 910 is coupled to an  
15 analog digital converter (ADC) 1215 through filter 1205. Similarly, the analog y signal from accelerometer 910 is coupled to ADC 1215 through filter 1210. Filter 1205 and filter 1210 filter out noise artifacts and cancel high frequency elements that may cause analog to digital aliasing. Filter 1205 and  
20 filter 1210 may be partially implemented using digital signal processing within controller 940.

ADC 1215 converts analog signals from filter 1205 and filter

1210 to digital signals. ADC 1215 may be external to controller 940 or may be incorporated within controller 940.

Similarly, the analog -y (i.e., negative y) signal from accelerometer 920 is coupled to ADC 1215 through filter 1225. The analog z signal from accelerometer 920 is coupled to ADC 1215 through filter 1230. Filter 1225 and filter 1230 also filter out noise artifacts and cancel high frequency elements that may cause analog to digital aliasing. Filter 1225 and filter 1230 may be partially implemented using digital signal processing within controller 940.

Controller 940 uses the x, y, z acceleration values to calculate values for the x, y, z distances. This calculation is done by first calculating a time integral of the x, y, z acceleration values to obtain x, y, z velocity values. Then a time integral of the x, y, z velocity values is calculated to obtain the x, y, z distance values. Controller 940 then uses Equations (4), (5), and (6) to calculate the spherical polar (SP) coordinates  $R$ ,  $\Theta$ ,  $\Phi$ . Controller 940 then sends the digital form of the  $R$ ,  $\Theta$ ,  $\Phi$  coordinates to digital to analog converter (DAC) 1240. DAC 1240 converts the digital form of the  $R$ ,  $\Theta$ ,  $\Phi$  coordinates into an analog form. DAC 1240 may be external to controller 940 or may be incorporated within controller 940.

The analog  $R$  signal is filtered in filter 1250. The analog



$\Theta$  signal is filtered in filter 1260. The analog  $\Phi$  signal is filtered in filter 1270. The filtered R,  $\Theta$ ,  $\Phi$  signals are the spherical polar (SP) components of a vector that represents a measurement of the location of the body to which accelerometer 910 and accelerometer 920 are attached.

5 In one advantageous embodiment of the present invention, controller 940 uses indicating means 41 to transmit the SP coordinates to RF receiver 115 and processor 117 (as shown in FIGURE 7). As previously mentioned, RF receiver 115 is tuned to receive transmissions from indicating means 41. As will be more fully described, processor 117 is capable of analyzing the  
10 SP coordinate information that it receives from controller 940.

As time passes, the body to which accelerometer 910 and accelerometer 920 and controller 940 are attached moves (or does not move). Therefore, controller 940 continually sends to  
15 processor 117 a stream of SP coordinates that represent the motion of the body. Memory 121 attached to processor 117 contains a library of prerecorded sets of SP coordinates in which each prerecorded set of SP coordinates represents a type of motion.

For example, a first prerecorded set of SP coordinates  
20 could represent inactivity or the absence of motion (i.e., "no motion"). The absence of motion could signify the existence of a problem condition. If the body to which accelerometer 910

and accelerometer 920 and controller 940 is attached is a person, then a "no motion" signal could mean that (1) the person has become unconscious and has ceased moving, or that (2) the sensor device has become detached from the person, or that (3) the sensor device has ceased to function properly, or the like.

5           A second prerecorded set of SP coordinates could represent a successful attempt to change position. A third prerecorded set of SP coordinates could represent an unsuccessful attempt to change position.

10           A fourth prerecorded set of SP coordinates could represent the motion of a body moving with a particular type of gait, and especially a gait that is associated with a disability (e.g., limping). The term "moving" generally refers to all types of motion such as walking, running, skipping, jogging, jumping, and other types of motion.

15           A fifth prerecorded set of SP coordinates could represent the motion of a person who is unsteady and is swaying back and forth.

20           A sixth prerecorded set of SP coordinates could represent the motion of a person who experiences a "near fall." A near fall occurs when a person loses his or her balance but recovers in time to keep from actually falling. A seventh prerecorded set of SP coordinates could represent the motion of a person who experiences an actual fall.

A series of different types of motion may be recorded in which each type of motion is represented by a prerecorded set of SP coordinates.

Processor 117 analyzes the SP coordinate information that it receives from controller 940 by comparing it with each  
5 prerecorded set of SP coordinates stored in memory 121. When processor 117 identifies a match between the measured set of SP coordinates from controller 940 and one of the prerecorded sets of SP coordinates stored in memory 121, then processor 117 generates and sends a message that a match has been found.

10 The message may be sent by audible alarm 123, LED bank 107 and/or retransmission unit 125. In this manner, controller 940 identifies types of motions that the body experiences including, without limitation, falls, near falls and particular types of gaits of motion.

15 The ability of processor 117 to detect patterns of motion that typically precede a fall is very useful in preventing falls. For example, an elderly or infirm person who attempts to rise from a bed or chair may be subject to falling. Assume that processor 117 detects a pattern of motion that typically occurs  
20 before a fall when a person is attempting to rise from a bed or a chair. Processor 117 can then activate an alarm to alert the person that a fall may be imminent. Upon hearing the alarm, the

person is warned to cease his or her attempt to rise. A nearby care giver may also hear the alarm and come to assist the person before a fall occurs. In this manner serious falls can be prevented.

In an alternate advantageous embodiment of the present invention, controller 940 contains the library of prerecorded sets of SP coordinates. In this embodiment, controller 940 performs the analysis of the SP coordinate data. When a match is found, controller 940 generates and sends a message (using indicating means 41) that a match has been found. An alarm may then be sounded in the manner previously described.

FIGURE 13 illustrates a flow diagram showing a first portion of an advantageous embodiment of the method of the present invention. The steps of the first portion of the method are collectively referred to with the reference numeral 1300. At the start of the method, accelerometer 910 and accelerometer 920 measure the x, y, z values of acceleration (step 1310). Controller 940 then calculates the x, y, z distance values (step 1320). Controller 940 then converts the x, y, z distance values to spherical polar (SP) coordinates (step 1330).

Processor 117 (or controller 940 in an alternative embodiment) compares a measured set of SP coordinates with each of the plurality of prerecorded sets of SP coordinates that

represents a type of motion (step 1340). Processor 117 (or controller 940 in an alternative embodiment) identifies a match between the measured set of SP coordinates and one particular prerecorded set of SP coordinates that represents a type of motion (step 1350). Processor 117 (or controller 940 in an alternative embodiment) then sends a message that a match has been found (step 1360).

FIGURE 14 illustrates a flow diagram showing a second portion of an advantageous embodiment of the method of the present invention. The steps of the second portion of the method are collectively referred to with the reference numeral 1400.

The second portion of the method uses the SP coordinate data to calculate a value for a static acceleration vector that represents the value of the earth's gravitational acceleration. When an object falls in a vacuum (i.e., an environment where there is no frictional force due to air resistance) the sum of the components for the static acceleration vector is zero.

When a person loses his or her balance and falls, the measurement of the static acceleration vector that controller 940 records is not zero. The measured value is less than one "g" but is greater than a zero value. The value is greater than zero because the person's muscle tone (due to the slight contraction of skeletal muscles that is always present) operates to slow the

person's body a little bit as the body falls. In some cases, objects may impede the person's fall or the person may reflexively grasp some object to slow the rate of fall.

When the value of the static acceleration vector reaches a value that is less than one "g" but greater than a zero value, that is an indication that controller 940 has experienced a fall. Unlike some types of prior art methods (e.g., tilt switches), this method of detecting a fall does not rely on detecting a change in the angle of orientation of the body. The occurrence of a fall is detected by detecting a reduction in the value of the static acceleration vector to a value that is less than one "g."

If controller 940 was not connected to a person's body during the fall, then the value of the static acceleration vector measured by controller 940 after the fall will instantaneously be equal to one "g." If controller 940 was connected to a person's body during the fall, then the value of the static acceleration vector measured by controller 940 after the fall will rise relatively slowly. This is due to the fact that the person's muscle tone (due to the slight contraction of skeletal muscles that is always present) operates to slow the rise of the value of the static acceleration vector after the fall.

If the value of the static acceleration vector rises at a

rate that is greater than a preselected threshold rate, then it is clear that controller 940 was not connected to a person's body during the fall. If the value of the static acceleration vector rises at a rate that is less than a predetermined threshold rate, then it is clear that controller 940 was connected to a person's  
5 body during the fall.

At the start of the second portion of the method of the present invention, controller 940 has converted the x, y, z distance values to spherical polar (SP) coordinates (step 1330). Controller 940 then uses the SP coordinates to calculate the  
10 value of the static acceleration vector (step 1410). Controller 940 determines whether the value of the static acceleration vector has reached a value that is less than one "g" (decision step 1420). If not, then controller 940 updates the SP coordinates (step 1430) and control returns to step 1410.

15 If the value of the static acceleration vector has reached a value that is less than one "g," then controller 940 determines the rate at which the value of the static acceleration vector is increasing from the value that is less than one "g" (step 1440). Processor 940 then compares the rate to a preselected threshold  
20 rate (decision step 1450). If the rate is greater than the preselected threshold rate, then controller 940 sends a message that controller 940 was not connected to the person's body during

the fall (step 1470). If the rate is not greater than the preselected threshold rate, then controller 940 sends a message that controller 940 was connected to the person's body during the fall (step 1460). In this manner controller 940 is able to distinguish between a fall of controller 940 alone and a fall of controller 940 while controller 940 was coupled to a person's body.

Relatively rare instances may occur in which controller 940 will require additional information to distinguish between a fall of controller 940 alone and a fall of controller 940 while controller 940 is coupled to a person's body. As previously described, the measured value of acceleration of a falling person is usually less than one "g" but is greater than a zero value. The value is greater than zero because the person's muscle tone (due to the slight contraction of skeletal muscles that is always present) operates to slow the person's body a little bit as the body falls. This is true for normal falling situations.

However, it is not true in the relatively rare cases in which the falling person's body is not in contact with any object. For example, if a person falls off a ladder, then the person's body falls through the atmosphere and does not make contact with any object until impact with the floor or ground. In this type of fall the falling person's muscle tone does not operate to slow the person's body during the fall because the person is not in contact



with an external object.

An alternate advantageous embodiment of the present invention can detect this type of fall. In the alternate embodiment controller 940 detects an additional signal to determine whether controller 940 was coupled to the falling person's body.

5 For example, as previously described, controller 940 comprises processing circuitry 39 that is capable of receiving a signal from respiration module 73. Respiration module 73 is capable of detecting the respiration rate of the falling person.

10 In an alternate embodiment of the present invention, controller 940 detects a rate at which the value of the static acceleration vector is increasing from a value that is less than one "g". If the detected rate is greater than a preselected threshold rate (usually indicative of a fall of controller 940 not coupled to a body), then controller 940 determines whether a  
15 respiration signal was detected within a predetermined time period (e.g., six (6) seconds). If a respiration signal was detected, then processor 940 reports that the fall was a fall of controller 940 connected to a body and not a fall of controller 940 alone.

20 FIGURE 15 illustrates a flow diagram showing a third portion of an alternate advantageous embodiment of the method of the present invention. The steps of the third portion of the method are collectively referred to with the reference numeral 1500.

At the start of this portion of the method, accelerometer 910 and accelerometer 920 have measured the x, y, z values of acceleration (per step 1310 of FIGURE 13) and controller 940 has calculated the x, y, z distance values (per step 1320 of FIGURE 13).

5 Processor 117 (or controller 940 in an alternative embodiment) determines whether the current x, y, z distance values are the same as the prior x, y, z distance values (step 1510), to thereby determine whether system 11 has remained inactive between  
10 measurements. The meaning of the term "same," in the present instance, is determined by the application (i.e., the environment in which the body is monitored) performed by processor 117, and may mean exactly the same or substantially the same depending thereon.

If processor 117 determines that the current x, y, z distance values are the same as the prior x, y, z distance values ("YES" branch of step 1510), then processor 117 increases the counter  
15 (step 1520) and determines whether the counter is equal to at least one inactivity threshold value (step 1530). The "counter" may be any means for counting, calculating, enumerating or otherwise computing time or duration during which system 11 remains inactive.  
20 Again, "inactivity" is likewise determined by the application performed by processor 117.

If processor 117 determines that the counter is equal to at

least one inactivity threshold value ("YES" branch of step 1530), then processor 117 reports the occurrence of an inactivity event (step 1540). Hence, processor 117 has determined that the body activity level has remained relatively small to inactive for near to or at a threshold time period. Again, depending upon the application, then processor 117 is operable to respectively generate one of a warning signal and an alarm signal. System 11 can, for instance, be used to monitor and measure body motions (accelerations [at variable levels, e.g., .1g, .2g ....], angle changes [at variable levels, e.g., 15 degrees, 20 degrees.....], or both).

If processor 117 determines that the current x, y, z distance values are not the same as the prior x, y, z distance values ("NO" branch of step 1510), then processor 117 resets the counter (step 1550).

If processor 117 has reset the counter (step 1550) or determine that the counter does not equal at least one inactivity threshold value ("NO" branch of step 1530), then processor 117 sets the prior x, y, z distance values equal to the current x, y, z distance values (step 1560). Controller 940 now proceeds to convert the x, y, z distance values to spherical polar (SP) coordinates (per step 1330 of FIGURE 13).

Although the present invention has been described in detail, those skilled in the art should understand that they can make various changes, substitutions and alterations herein without departing from the spirit and scope of the invention in its broadest form.

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
2208  
2209  
2210  
2211  
2212  
2213  
2214  
2215  
2216  
2217  
2218  
2219  
2220  
2221  
2222  
2223  
2224